



What Subs Go With My Amp?

Let MTX help you out. This chart shows all current MTX mono block subwoofer amplifiers in the top row and all subwoofer models in the left column. The highest number of subs and lowest impedance is shown in the chart for the models that are optimized to work together.

If you still have questions give our tech support team a call at 1-800-CALL-MTX.



MODEL	TE4001D	TE1501D	TE801D	TE601D	TH1200.1D	TH650.1D	TH350.1D	TD1000.1D	TD500.1D	TN250/1
TS9924-22	1 (1Ω)									
T9922-22	1 (1Ω)									
T815-22		3 (1.34Ω)	2 (2Ω)		2 (2Ω)					
T815-44	4 (2Ω)			1 (2Ω)		1 (2Ω)		2 (1Ω)	1 (2Ω)	
T812-22		3 (1.34Ω)	2 (2Ω)		2 (2Ω)					
T812-44	6 (1.3Ω)					1 (2Ω)		2 (2Ω)	1 (2Ω)	
T810-22		4 (1Ω)	2 (2Ω)	2 (2Ω)			1 (1Ω)	2 (2Ω)		
T810-44	8 (1Ω)				3 (2.67Ω)	1 (2Ω)				
RTS15-04					4 (1Ω)	3 (1.67Ω)		4 (1Ω)	2 (2Ω)	
RTS15-44			3 (2.67Ω)		4 (2Ω)		1 (2Ω)	4 (2Ω)		1 (2Ω)
RTS12-04					4 (1Ω)	3 (1.67Ω)		4 (1Ω)	2 (2Ω)	
RTS12-44			4 (2Ω)		4 (2Ω)		1 (2Ω)	4 (2Ω)		1 (2Ω)
RTS10-04						3 (1.67Ω)		4 (1Ω)	2 (2Ω)	2 (2Ω)
RTS10-44			4 (2Ω)		4 (2Ω)		1 (2Ω)	4 (2Ω)		
RTS08-04							2 (2Ω)			1 (4Ω)
RTS08-44						3 (2.67Ω)		6 (1.33Ω)	3 (2.67Ω)	1 (2Ω)
RTL15-04						3 (1.67Ω)	2 (2Ω)	3 (1.67Ω)	2 (2Ω)	
RTL15-44		8 (1Ω)		2 (4Ω)	8 (1Ω)					1 (2Ω)
RTL12-04						3 (1.67Ω)	2 (2Ω)	3 (1.67Ω)	2 (2Ω)	
RTL12-44		8 (1Ω)	4 (2Ω)	2 (4Ω)	8 (1Ω)					1 (2Ω)
RTL10-04						3 (1.67Ω)	2 (2Ω)	3 (1.67Ω)	2 (2Ω)	
RTL10-44			4 (2Ω)	2 (4Ω)	8 (1Ω)					1 (2Ω)
TN12-04						3 (1.33Ω)	1 (4Ω)	3 (1.67Ω)	2 (2Ω)	2 (2Ω)
TN12-02			4 (2Ω)		4 (2Ω)					1 (2Ω)
TN10-04							2 (2Ω)		2 (2Ω)	2 (2Ω)
FPR12-04		4 (1Ω)	2 (2Ω)	2 (2Ω)	4 (1Ω)	2 (2Ω)		4 (1Ω)	2 (2Ω)	
FPR12-02	8 (1Ω)	4 (2Ω)			4 (2Ω)	2 (1Ω)	1 (2Ω)	4 (2Ω)		1 (2Ω)
FPR10-04				2 (2Ω)	4 (1Ω)	2 (2Ω)		4 (1Ω)	2 (2Ω)	
FPR10-02							1 (2Ω)			1 (2Ω)